



SURVIVOR USER GUIDE

DreamWave Audio USA, LLC
www.godreamwave.com

What's in the box

- Survivor X 1
- Ac adaptor X 1
- User guide X 1
- AUX cable X 1
- Warranty card x 1
- Jump Start Cable x 1

Product Introduction

AUX-IN

Bluetooth

NFC Connection

Hands-free

Charge mobile devices

Battery Capacity Indicator

Press the Power button lightly to check the remaining battery capacity.

| Indicator lights | Battery Capacity |
|------------------|------------------|
| 5 off | 0% |
| 1 Solid ON | 20% |
| 2 Solid ON | 40% |
| 3 Solid ON | 60% |
| 4 Solid ON | 80% |
| 5 Solid ON | 100% |

LED flashlight (2 illumination modes)

Press the Power Button for 3 seconds to turn on the LED light, hold on for 3 seconds to enter SOS mode (quick flash), press again to turn off (solid on -> SOS -> OFF)

Jump start a vehicle

- Make sure the remaining battery capacity of power bank is above 50% (there should be at least 3 indicator lights being ON.)
- Connect the jump start cable to the drained battery of the vehicle, the connection must be red clamp to battery "+", black clamp to battery "-".
- Connect the jump start cable to the power bank (just plug the proper end of the jump start cable into the "Jump Start Socket" on the power bank).
- You can now crank the engine, if the engine does not start, disconnect the clamps from the vehicle battery and wait at least 10 seconds before reconnecting the clamps to attempt crank starting the engine again.
- Disconnect the jump start cable from the power bank within 10 seconds after the vehicle engine has been successfully started, and then remove the clamps from the battery terminals.

Technical information

- Power: 30w
- Car battery jump starter function, max jump start current: 400 A
- CSR 4.0+EDR, A2DP, AVRCP, APTX
- LED flashlight, 100 - 110 lumens
- Rechargeable Li-Polymer battery 12000mAh, 7 hours play time at max volume, full bass status
- NFC
- USB port 5V/1A output rechargeable power bank for mobile devices. 3.7V / 12000mAh (11.1V/4000mAh = 44.4Wh)
- HFC (Hands free calling)
- IPX5 splashproof
- SIZE: 174 x 390 x 130 mm / 6.85 x 15.35 x 5.12 inch
- NET Weight: 3300 g / 3.3 KG / 7.26 lb / 116.391 oz

EN

Bluetooth Version: 4.0 + EDR
Bluetooth Chipset: CSR
Support: A2DP, AVRCP, APTX, NFC
Hi-Fi digital amplifier, Anti-distortion
Handsfree speakerphone
5V/1A power bank (44.4Wh)
400A Emergency Car Battery Jump Starter
110 Lumens LED Flashlight w/SOS Flash
IPX5, splashproof
Power: 30W
Frequency response: 50Hz-18kHz
SN Ratio: 75dB
Battery type: Li-polymer 3.7V / 12000mAh (11.1V/4000mAh)
Music playing time: 7hrs at max volume, full bass status
Dimensions: H174xW390xD130(mm)/ 6.85 x 15.35 x 5.12 inch
Weight: 3300 g / 3.3 KG / 7.26 lb / 116.391 oz

JP

Bluetoothバージョン: 4.0 + EDR
Bluetoothチップ: CSR
対応プロファイル: A2DP, AVRCP, APTX, NFCファンクション
Hi-Fiサウンド、アンチディストーション回路
ハンズフリー
5V/1A パワーバンク (44.4Wh)
400A 自動車緊急起動用
110ルーメンLED懐中電灯 (SOSフラッシュ付き)
防水性能: IPX5、防水
定格出力: 30W
再生周波数: 50Hz-18kHz
SNレシオ: 75dB
バッテリー・タイプ: リチウムリオン3.7V / 12000mAh (11.1V/4000mAh)
連続再生時間: 最大音量で7時間
寸法: H174xW390xD130(mm)/ 6.85 x 15.35 x 5.12 inch
重量: 3300 g / 3.3 KG / 7.26 lb / 116.391 oz

DK

Bluetooth Version: 4.0 + EDR
Bluetooth Chip: CSR
Understøtter: A2DP, AVRCP, APTX, NFC
Hi-Fi digital forstærker, Anti-forvrængning
Håndfri højttalertelefon
5V/1A power bank (44.4Wh)
110 lumen LED lommelygte m / SOS Flash
400A bil nød batteri starter
IP rate: IPX5, splashproof
Effekt: 30W
Frekvensområde: 50Hz-18kHz
Signal/støj forhold: 75dB
Battery type: Li-polymer 3.7V / 12000mAh (11.1V/4000mAh)
Afspilningstid: 7 timer ved max volume og fuld bas
Dimensioner: H174xW390xD130(mm)/ 6.85 x 15.35 x 5.12 inch
Vægt: 3300 g / 3.3 KG / 7.26 lb / 116.391 oz

FR

Bluetooth Version: 4.0 + EDR
Bluetooth Chip: CSR
soutien: A2DP, AVRCP, APTX, NFC
Hi-Fi digital amplificateur, sans distorsion
mains libre appel
5V/1A puissance mobile (44.4Wh)
400 A Kfz Starthilfe Option
Lampe LED SOS clignotante de 110 Lumens
Chargeur rapide d'urgence pour batterie de voiture de 400A
IP niveau: IPX5, etanche
Puissance: 30W
Frequence: 50Hz-18kHz
SN taux: 75dB
Batterie type: Li-polymer 3.7V / 12000mAh (11.1V/4000mAh)
Temps de lecture: 7 heures en maximum volume
Dimensions: H174xW390xD130(mm)/ 6.85 x 15.35 x 5.12 inch
Poids: 3300 g / 3.3 KG / 7.26 lb / 116.391 oz

ES

Bluetooth versión: 4.0 + EDR
Bluetooth chipset: CSR
Apoyo: A2DP, AVRCP, APTX, NFC
Hi-Fi amplificador digital, Anti-distorsion
altavoz manos libres
5V/1A banco de potencia (44.4Wh)
bateria de emergencia de 400A para arranque del coche
110 lúmenes linterna LED w / SOS de Flash
tasa de IP: IPX5, a prueba de salpicaduras
Potencia nominal: 30W
Respuesta de frecuencia: 50Hz-18kHz
Proporción de SN: 75dB
tipo de batería: iones de litio 3.7V / 12000mAh (11.1V/4000mAh)
tiempo de reproducción de música: 7 en el volumen máximo, estado completo bajo
Dimensiones: H174xW390xD130(mm)/ 6.85 x 15.35 x 5.12 inch
Peso: 3300 g / 3.3 KG / 7.26 lb / 116.391 oz

DE

Bluetooth Version: 4.0 + EDR
Bluetooth Chipsatz: CSR
Support: A2DP, AVRCP, APTX, NFC
Hi-Fi digitaler Verstärker, Gegen Verzerrung
Freisprecheinrichtung
5V/1A Akku (44.4Wh)
400 A Kfz Starthilfe Option
110 Lumen LED Blitzlicht mit SOS Blinklicht
IPX5, spritzwasser geschützt
IP rate: IPX5, spritzwasser geschützt
Power: 30W
Frequenz: 50Hz-18kHz
SN Verhältnis: 75dB
Batterietyp: Li-Polymer 3.7V / 12000mAh (11.1V/4000mAh)
Musik Wiedergabezeit: 7 Stunden bei max Lautstärke, volle Bässe
Abmessungen: H174xW390xD130(mm)/ 6.85 x 15.35 x 5.12 inch
Gewicht: 3300 g / 3.3 KG / 7.26 lb / 116.391 oz

PL

Wersja Bluetooth: 4.0 + EDR
Chipset: CSR
Funkcje: A2DP, AVRCP, APTX, NFC
Cyfrowy wzmacniacz Hi-Fi, brak zniekształceń
Zestaw głośnomówiący
Power bank 5V/1A (44.4Wh)
400A Awaryjny rozrusznik do akumulatora samochodowego
Latarka LED o mocy 110 Lumenów z funkcją emitowania sygnału SOS
Stopień ochrony: IPX5, odporny na zachłapania
Moc znamionowa: 30W
Pasmo przenoszenia: 50Hz-18kHz
Stosunek sygnału do szumu (S/N): 75dB
Bateria: Litowo-polimerowa 3.7V / 12000mAh (11.1V/4000mAh)
Czas odtwarzania muzyki: 7 godz. z maksymalną głośnością i basem
Wymiary: H174xW390xD130(mm)/ 6.85 x 15.35 x 5.12 inch
Waga: 3300 g / 3.3 KG / 7.26 lb / 116.391 oz

RU

Версия Bluetooth: 4.0 + EDR
Bluetooth чип: CSR
Поддерживает: A2DP, AVRCP, APTX, NFC
Hi-Fi цифровой усилитель, защита от искажений
Беспроводной микрофон
5V/1A аккумулятор (44.4Wh)
400A источник питания для зарядки автомобильного аккумулятора
110 лм LED фонарь с SOS сигналом
Степень защиты (IP): IPX5, защита от брызг
Мощность: 30W
Частотная характеристика: 50Hz-18kHz
Отношение сигнал/шум: 75dB
Тип батареи: Литий-ионная 3.7V / 12000mAh (11.1V/4000mAh)
Продолжительность проигрывания: 7 часов при максимальной громкости
Параметры: H174xW390xD130(mm)/ 6.85 x 15.35 x 5.12 inch
Вес: 3300 g / 3.3 кг / 7.26 lb / 116.391 oz

CHT

藍牙版本: 4.0 + EDR
藍牙晶片: CSR
支持: A2DP, AVRCP, APTX, NFC
Hi-Fi數字功放
免提通話
5V/1A內置移動電源 (44.4Wh)
110 流明LED 照明 / sos
電池汽車啟動最大電流: 400A
防水等級: IPX5
功率: 30W
頻率: 50Hz-18kHz
信噪比: 75dB
電池: 3.7V / 12000mAh (11.1V/4000mAh) 聚合物電池
播放時長: 最大音量下續航7小時
產品尺寸: H174xW390xD130(mm)/ 6.85 x 15.35 x 5.12 inch
產品淨重: 3300 g / 3.3 KG / 7.26 lb / 116.391 oz

CHS

藍牙版本: 4.0 + EDR
藍牙晶片: CSR
支持: A2DP, AVRCP, APTX, NFC
Hi-Fi數字功放
免提通話
5V/1A內置移動電源 (44.4Wh)
110 流明LED 照明 / sos
汽車啟動最大電流: 400A
防水等級: IPX5
功率: 30W
頻率: 50Hz-18kHz
信噪比: 75dB
電池: 3.7V / 12000mAh (11.1V/4000mAh) 聚合物電池
播放時長: 最大音量下續航7小時
產品尺寸: H174xW390xD130(mm)/ 6.85 x 15.35 x 5.12 inch
產品淨重: 3300 g / 3.3 KG / 7.26 lb / 116.391 oz

Trouble shooting

- Applicable To: All DreamWave Bluetooth speakers.
- The trouble shooting steps in this article apply if audio is intermittent, crackling or distorted when streaming via Bluetooth.

- Try playing other audio files. Ensure that audio can play fine from the same audio device when using a headphone.
- If Step 1 is not the case, try listening to audio by connecting the speaker to the Bluetooth device using the Aux-in cable. This will isolate if it's a Bluetooth connection issue or not. Remember to disconnect/un-pair the Bluetooth connection first.
- If the issue only happens when connecting via Bluetooth, do the following:
 - Check that you are connected to the correct speaker (i.e. select "Survivor" within the Bluetooth list on your device).
 - Check that the volume is not set to minimum.
- Ensure that the distance between the speaker and the Bluetooth device is with the distance of 10 meters.
- Turn the speaker off and turn it on again to reset the speaker.
- Further isolate the problem, do please shut down all other surrounding Bluetooth devices.
- Try to re-pair the speaker with the Bluetooth device.

If the problem still persist when connecting either to Bluetooth or Aux-in, please contact Dreamwave Customer Support via email.

IC ID: 21889-LB288
FCC ID: 2AD2BLB288
Patent: ZL201530219021.8 / ZL201520316330.1